


20V MAX ANGLE GRINDER

3500006 - Instruction Manual



CAUTION: Using this product with 1.5Ah Battery or 2.0Ah Battery can cause the Battery to overheat.

CONTENTS

Safety Instructions

1

Safety Instructions

2

Safety Instructions

3

Safety Instructions

4

Safety Symbols

5

Specification

6

Battery Capacity Indicator, Charging Lights

7

Attaching the Safety Guard and Grinding Disc

8

Battery Insertion/Removal, Powering On/Off

9

Care & Maintenance, Troubleshooting

10

User Notes

11

Warranty

12

WARNING

PLEASE READ THESE INSTRUCTIONS CAREFULLY AND KEEP FOR FUTURE REFERENCE

GENERAL SAFETY INFORMATION.

WARNING! Read all safety warnings and all instructions. Failure to follow the warnings and instructions may result in electric shock, fire and/or serious injury. Please retain all warnings and instructions for future reference.

The term "power tool" in the warnings refers to your mains-operated (corded) power tool or battery-operated (cordless) power tool.

INTENDED USE.

This 20 Max Angle Grinder is not intended for use by persons with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instructions concerning use of the tool by a person responsible for their safety. Children should be supervised to ensure they do not play with the tool.

WORK AREA SAFETY.

Keep your work area clean and well lit. Cluttered or dark areas invite accidents. Do not operate power tools in explosive atmospheres such as in the presence of flammable liquids, gases or dust. Power tools create sparks which may ignite the dust or fumes.

Keep bystanders, children and animals away whilst operating the power tool. Distractions can cause you to lose control.

ELECTRICAL SAFETY.

Avoid body contact with earthed or grounded surfaces such as pipes, radiators, ranges and refrigerators. There is an increased risk of electric shock if your body is earthed or grounded. Do not expose power tools to rain or wet conditions. Water entering the power tool will increase the risk of electric shock.

BEFORE USE.

Use personal protective equipment. Always wear eye protection. Protective

equipment such as a dust mask, non-skid safety shoes, hard hat, or hearing protection used for appropriate conditions will reduce personal injuries. Dress appropriately. Do not wear loose clothing or jewellery. Keep your hair, clothing and gloves away from moving parts to prevent them from becoming caught in the tool.

If devices are provided for the connection of dust extraction and collection facilities, ensure that these are connected and properly used to reduce dust-related hazards.

POWER TOOL USE AND CARE.

Prevent unintentional starting. Ensure the switch is in the off position before picking up or carrying the tool. Carrying power tools with your finger on the switch, or energising power tools that are switched on, invites accidents.

Do not use the power tool if the switch does not turn it on and off. A power tool that cannot be controlled with the switch is dangerous and must be repaired. Use the power tool, accessories and tool bits etc. in accordance with these instructions, taking into account the working conditions and the work to be performed. Use of the power tool for operations different from those intended could result in a hazardous situation.

WARNING! Use only accessories recommended for this tool. Follow the instructions that accompany the accessories. The use of improper accessories may result in injury to the operator or damage the tool.

WARNING! If any part is missing or damaged, do not plug the tool into the power source or install any accessory until the missing or damaged part is replaced. Failure to follow this instruction could result in serious personal injury.

WARNING

PLEASE READ THESE INSTRUCTIONS CAREFULLY AND KEEP FOR FUTURE REFERENCE

Stay alert, watch what you are doing and use common sense when operating a power tool. Do not use a power tool while you are tired or under the influence of drugs, alcohol or medication. A moment of inattention while operating power tools may result in serious personal injury.

Do not force the power tool. Use the correct power tool for your application. The correct power tool will do the job better and safer at the rate for which it was designed.

Do not overreach. Keep proper footing and balance at all times. This will enable better control of the power tool in unexpected situations.

AVOIDING KICKBACK

Maintain a firm grip on the power tool and position your body and arm to allow you to resist kickback forces. Always use the auxiliary handle, if provided, for maximum control over kickback or torque reaction during start up.

The operator can control torque reactions or kickback forces, if proper precautions are taken.

Never place your hand near the rotating accessory the accessory may kickback over your hand.

Do not position your body in the area where power tool will move if kickback occurs. Kickback will propel the tool in the direction opposite to the wheel's movement at the point of snagging.

Use special care when working corners, sharp edges etc. Avoid bouncing and snagging the accessory. Corners, sharp edges or bouncing have a tendency to snag the rotating accessory and cause loss of control or kickback.

MAINTENANCE & STORAGE.

Maintain the power tool. Check for misalignment or binding of moving

parts, breakage of parts and any other condition that may affect the power tool's operation. If damaged, have the power tool repaired before use. Many accidents are caused by poorly maintained power tools.

Store idle power tools out of reach of children and do not allow persons unfamiliar with the power tool or these instructions to operate the power tool. Power tools are dangerous in the hands of untrained users.

SERVICE.

Have your power tool serviced by a qualified repair person using identical replacement parts only to ensure that the safety of the power tool is maintained.

IMPORTANT PRODUCT CARE INFORMATION.

This tool uses Lithium-ion battery cells. Care **MUST** be taken to ensure both the safety and life of the battery is maintained. Ensure you have read all of the safety information in the previous pages before using the tool.

Safety devices and circuitry for this tool are located in the battery of this tool. The battery is a vital component, not just for the power source, but also for the full safety control for both the charging and tool operation.

Avoid overloading the tool during operation.

NOTE: The battery is more susceptible to overloading when at the lower end of the charge.

ADDITIONAL SAFETY INFORMATION FOR THE CHARGER.

This tool is powered by Lithium-ion batteries which may only be charged with the specifically designed Lithium-ion battery charger purchased with this tool.

Do not attempt to charge the battery with any charger other than the one

⚠ WARNING ⚠

PLEASE READ THESE INSTRUCTIONS CAREFULLY AND KEEP FOR FUTURE REFERENCE

supplied as this is potentially dangerous. Do not plug anything other than the supplied battery into the charger as other objects may touch dangerous voltage points or short out parts which may result in fire or electric shock.

Before using the charger, read all instructions, labels and cautionary markings on the charger and battery, as well as the instructions on using the battery.

Do not use the charger if it has been subjected to a heavy knock, dropped or otherwise damaged in any way. Take the charger to an authorised service centre for it to be checked and repaired.

DANGER! If the battery is cracked or damaged in any way, do not insert it into the charger.

Do not attempt to disassemble the charger. Opening or removing covers may expose you to dangerous voltages or other risks. Incorrect reassembly may result in the risk of fire or electric shock. If there is a problem with the battery or tool, take it to your nearest authorised service centre.

Take the tool or charger to your nearest authorised service centre:

If liquid has been spilled into the tool or charger, or if rain or water has touched the tool or charger.

If the tool or charger does not operate normally after you follow the operating instructions.

If the tool or charger exhibits a distinct degradation in performance.

If the tool or charger is damaged in any way.

If the battery is not charged within the time frame as specified in this manual, turn the charger off.

Use the battery charger indoors only.

Do not place the tool or charger on an

uneven surface as a fall may cause serious damage.

Do not operate the charger in a cabinet or other enclosure unless proper ventilation is provided.

Never place the tool or charger near or over a heat source such as radiator or heater.

Do not charge batteries or use the tool and battery in locations where the temperature may be below 0°C, or above 40°C such as inside sheds or metal structures.

The battery can be charged or operated at temperatures between 0°C and 40°C.

WARNING! Never charge your Lithium-ion battery below or above temperatures recommended as this may result in fire or serious damage to the battery.

The most suitable temperatures to charge the battery are between 20°C and 25°C.

Do not place any object onto the charger or allow any object to rest on the charger.

Make sure that the charger cable is positioned where it will not be stepped on, tripped over or otherwise subjected to damage or stress. Keep the lead away from operating machinery.

Do not use an extension cord unless absolutely necessary. The use of an improper extension cord could result in fire or electric shock.

Never attempt to connect two chargers together.

WARNING! Do not allow water or any other liquid to come into contact with the charger as this may result in electric shock. Do not position the tool or battery charger near water. Take care not to spill liquid of any kind on the tool or charger.

To reduce the risk of electric shock, unplug the charger from the power supply before attempting to clean it. To clean the tool or charger, wipe with a

⚠️ WARNING ⚠️

PLEASE READ THESE INSTRUCTIONS CAREFULLY AND KEEP FOR FUTURE REFERENCE

damp cloth. Use of any other cleaners is not recommended.

Do not pull on the lead of the charger to disconnect it from the mains power socket.

ADDITIONAL SAFETY INFORMATION RELATED TO BATTERY SAFETY.

Use only the battery supplied with this tool or DOMU Brands approved replacements.

Do not use the battery to power any device other than the tool it was sold with.

Charge the battery only with the charger supplied with the tool or approved replacements and according to the instructions in this manual.

Do not charge the battery in a place where static electricity is generated, or let the battery touch anything that is statically charged.

Handle batteries with care to avoid shorting the battery with conducting materials such as nails, screws, metal watches, hands, rings, bracelets and keys. The battery may overheat and could cause burns.

Never attempt to open the battery, puncture the battery, or subject the battery to strong physical shock.

Stop using the product if it exhibits abnormal heat, odour, colour, deformation, or is in an abnormal condition.

If you detect leakage or a foul odour, it is especially important to keep the battery away from fire. If battery liquid leaks onto your skin or clothes, wash well with clean water immediately. If liquid leaking from the battery leaks into your eyes, do not rub your eyes; rinse eyes well (for at least 10 minutes) with clean water, and consult a doctor immediately. Never use a leaking battery.

Always allow the battery to cool down after charging. Do not leave in a hot environment.

Take care where the tool is stored. Do not store in areas of corrosive fumes, or salt air or similar conditions. Try to store the tool in the packaging it is supplied in.

WARNING! Never store or leave your Lithium-ion battery in temperatures over that recommended as this may result in fire.

Do not store the Lithium-ion battery anywhere that the temperature can easily reach temperatures higher than recommended (garden sheds, vehicles in direct sunlight etc.) Think before leaving your Lithium-ion battery in storage.

Do not dispose of the battery in a fire, or put the battery into a microwave oven, conventional oven, dryer or high-pressure container, as the battery may explode under these conditions.

After it has reached the end of its useful life, we recommend recycling the battery at your local municipal council recycling centre. **DO NOT** attempt to replace the battery cells in the product or repair or modify any part of the battery assembly. When recycling, make the battery non-conductive by applying insulating tape to the terminals located on the battery.

WHEN TO CHARGE THE BATTERY.

The battery should be fully charged before use.

The battery can be recharged at any time during use, provided the pack is not overheated.

If the battery starts to cut out due to low voltage, or tasks previously undertaken can no longer be performed, it is recommended to stop using the tool and recharge the battery.

SAFETY SYMBOLS

The following safety symbols may appear on this product. Please ensure you understand their meanings before operating this product in order to prevent personal injury and avoid damage to the tool.



WARNING! Pay attention to all safety and guidance



Read manual before use



Wear eye and ear protection



Wear a dust mask



Wear protective gloves

DECLARATION OF CONFORMITY


We:
DOMU Brands Ltd
5th Floor The Tower
Deva City Office Park
Manchester
M3 7BF

Declare under our sole responsibility that the product:
SKU: 3500006
Description: VonHaus 20V Max Angle Grinder
To which this declaration relates is in conformity with the following directives:

2014/30/EU, 2014/35/EU, 2006/42/EC, 2011/65/EU, 2013/56/EC

SPECIFICATION


CHARGER OUTPUT	BATTERY	BATTERY TYPE	DISC DIAMETER
V 21V $\frac{1}{2}$ 2.4A	V 20 Max	Li-ion	Ømm 115



1. Shoe
2. Spindle Lock
3. Handle Thread
4. ON/OFF Switch/Safety Switch
5. Outer Washer
6. Inner Washer
7. Handle with Spanner Storage
8. Spanner
9. Guard
10. Battery Charger
11. Charge Indication Lights
12. 20V Max Battery
13. Battery Release Button
14. Battery Level Indication
15. Battery Level Indication Button

BATTERY CAPACITY INDICATOR

When in use you can check the status of the 20V Max Battery (12) by pressing the Battery Level Indication Button (15). Pressing this will illuminate the 20V Max Battery's level of charge.



0-10% Charged



10-25% Charged



25-50% Charged



50-75% Charged



100% Charged

CHARGING LIGHTS

IMPORTANT if the battery does not fit properly, disconnect it and confirm that the battery pack is the correct model for this charger as shown on the specification chart. Do not charge any other battery pack or any battery pack that does not securely fit the charger.

Connect the Battery Charger (10) to the power outlet socket.

- Frequently monitor the Battery Charger and 20V Max Battery while connected.
- Unplug the Battery Charger (10) and disconnect it from the 20V Max Battery (13) when finished.
- Allow the 20V Max Battery (12) to cool completely before using it.
- Store the Battery Charger (10) and 20V Max Battery (12) indoors, and out of reach of children.


GREEN LIGHT	RED LIGHT	BATTERY ON THE CHARGER	CHARGING STATUS
ON	OFF	NO	Charger connected to power supply.
OFF	FLASHING	YES	Battery being charged.
ON	OFF	YES	Battery fully charged.
ON	ON	YES	Battery defective of faulty connection. Contact DOMU customer services.
ON	ON	YES	Battery too hot or too cold to be charged. Battery will begin to charge once the Battery has cooled sufficiently.

ATTACHING THE SAFETY GUARD & THE GRINDING DISK


WARNING! Always make sure that the Battery is removed from the Angle Grinder before making adjustments or performing maintenance to the tool.

Take the Guard (9) and slot over the Shoe (1). Align the notches and secure into place by closing the clip and then tightening the screw.


IMPORTANT: Ensure the Guard is in between the user and the blade.




Place the Inner Washer (6) onto the thread of the Shoe (1) and align the flat edges with those on the thread.




Place the Grinding Disc (10) over the Shoe (1) and rest it upon the Inner Washer (6).



Take the Outer Washer (5) and place the flat side against the Grinding Disc (10). Use the Spanner to tighten together.



To tighten, hold down the Spindle Lock (2) and turn the Grinding Disc until the Spindle Lock locates. Place the Spanner (8) over the corresponding holes and tighten whilst holding down the Spindle Lock.




BATTERY INSERTION/REMOVAL

WARNING! Before making any adjustments ensure the appliance is switched off or remove the 20V Max Battery (12).

Hold the Angle Grinder with one hand and the 20V Max Battery (12) with the other.

To install, push and slide 20V Max Battery into the battery port, make sure the Battery Release Button (13) of the 20V Max Battery snaps into place and is secure before beginning operation.

To remove, press the Battery Release Button and pull the 20V Max Battery out at the same time.




HANDLE ASSEMBLY

WARNING! Always make sure that the Battery is removed from the Angle Grinder before making adjustments or performing maintenance to the tool.

Before powering the Angle Grinder on/off, attach the Handle (7) on either side you work from and ensure it is tightened into place.

IMPORTANT: Always ensure you have a stable grip when using the Angle Grinder.




POWERING ON/OFF

WARNING! Always make sure that the Battery is removed from the Angle Grinder before making adjustments or performing maintenance to the tool.

To power on the Angle Grinder, press the Safety Switch down then the squeeze the ON/OFF Switch (4).

To power off the tool, push the ON/OFF Switch towards the rear of the tool.



CARE AND MAINTENANCE

WARNING! Always make sure that the Battery is removed from the Angle Grinder before making adjustments or performing maintenance to the tool.

To clean the Angle Grinder effectively, it is recommended to use compressed air. If unavailable, use a brush to remove dust and chips from the Saw.

IMPORTANT: Make sure to clean the ventilation outlets regularly so as to prevent the Saw from overheating.

Clean the exterior body of the tool with a soft damp cloth using mild detergent to remove dust. Dry thoroughly.

CAUTION: Never use any caustic agents - such as gasoline, carbon tetrachloride, chlorinated cleaning solvents, ammonia and household cleaners containing ammonia - to clean the body of the tool. Always check the tool for damage or wear before each use. In particular, inspect the Saw Disk for wear and replace if necessary.

Always store in a dry, frost-free place away from children.

TROUBLESHOOTING

PROBLEM	SOLUTION
TOOL DOES NOT POWER ON.	Check that the battery is correctly inserted. Brushes may be worn. Please contact a qualified engineer to have them replaced.
DISK DOES NOT MOVE.	The Disk may be blocked. Power off and remove the battery, safely remove the blockage. Check that the Disk is correctly fitted.
POOR PERFORMANCE.	Disk may have become worn. Replace as necessary. You may be using the wrong type of Disk for the material.
DISK BECOMES HOT.	There may be a blockage. Remove the battery and carefully remove the blockage.
DISK JUDDERING OR VIBRATING ABNORMALLY.	Check that there are no obstructions. Ensure the Disk has been put on securely Ensure the Clamp Bolt is securely fastened.

USER NOTES

Vonhaus

DISPOSAL INFORMATION

PRODUCT DISPOSAL INFORMATION

For electrical products sold within the European Community, at the end of the electrical product's useful life, it should not be disposed of with household waste. Please recycle where facilities exist.

Contact your local authority for details of collection schemes in your area.

In all circumstances:

- Do not dispose of in domestic waste.
- Do not incinerate.
- Do not abandon in the environment.
- Do not dispose of WEEE as unsorted municipal waste.



HEALTH AND SAFETY FOR BATTERIES

Do not put in fire or mutilate – cells may burst and release toxic material.

Do not short-circuit cells as this may cause fire or burns.

The battery must be removed from the appliance before being scrapped.

The battery is to be disposed of safely.

BATTERY DISPOSAL INFORMATION

Do not mutilate batteries as corrosive electrolytes and flammable materials will be released.

Do not incinerate – Danger of explosion and release of toxic fumes.

Do not dispose of batteries or cells in a charged condition.

Expired lithium-ion batteries must be recycled/disposed of in accordance with the appropriate regulation or legislation. They should be returned to your local warranty agent/stockist.



Li-ion

CUSTOMER SERVICE

If you are having difficulty using this product and require support, please contact hello@domu.co.uk

WARRANTY

To register your product and find out if you qualify for a free extended warranty please go to

www.Vonhaus.com/warranty.

Please retain a proof of purchase receipt or statement as proof of the purchase date.

The warranty only applies if the product is used solely in the manner indicated in the Warnings page of this manual, and all other instructions have been followed accurately. Any abuse of the product or the manner in which it is used will invalidate the warranty.

Returned goods will not be accepted unless re-packaged in its original packaging and accompanied by a relevant and completed returns form. This does not affect your statutory rights.

No rights are given under this warranty to a person acquiring the appliance second-hand or for commercial or communal use.

COPYRIGHT

All material in this instruction manual are copyrighted by DOMU Brands.

Any unauthorised use may violate worldwide copyright, trademark, and other laws.

Vonhaus

Thank you for purchasing the 20V Max Angle Grinder

VonHaus® is a registered trademark of DOMU Brands Ltd
Made in China for DOMU Brands Ltd M24 2RW